20dB in-line passive satellite amplifier with power pass

BZD2101

Article Information

Product Group:	ANTENNA
Sub Group:	AMPLIFIER
Article group:	F-CONNECTOR
Date of introduction:	October 2010
Number:	BZD2101
Product Name:	20dB in-line passive satellite amplifier with power pass
Usage:	20dB amplifier for boosting your signal.

Features & Benefits

20dB in line amplifer 950 -2400 Mhz with return power pass
Power pass 14-18V.
Suitable for wall mounting
950 - 2400 Mhz.

Technical Information

Length:	/
From Connector:	F-conn female
To Connector:	f-conn female

Power pass
5-2400 Mhz.

Package Contents

Amplifier

Logistical Information

Languages:	GB, DE, FR, NL, ES, IT, PT, DK, PL, SE, RU, CZ, HU, TR
Package size:	B1D
Qty on display hook:	6 pcs

	Quantity	Packaging (HxDxW)	Weight	Barcode
Product	1 pcs	0,110 x 0,030 x 0,110 m	0,000 Kg	8717587042256
Inner carton	10 pcs	0,000 x 0,000 x 0,000 m	0,000 Kg	8717587042263
Outer carton	120 pcs	0,000 x 0,000 x 0,000 m	0,000 Kg	8717587042270

Bandridge Europe N.V.
P.O. Box 2333
2301CH LEIDEN
The Netherlands
T: + 31 (0)71 89 00 20 0
F: + 31 (0)71 89 00 20 9
E: sales@bandridge.com
I: bandridgeportal.com

Specifications are subject to change without notice.